

MULTI-JACK DETECTOR

BACKGROUND OF THE INVENTION

Field of the Invention

The invention relates to a multi-jack detector, and more particularly to a
5 multi-jack detector for detecting states of jacks using a single I/O pin.

Description of the Related Art

Along with advances in technologies, a variety of types of jacks, such as
Line, Surround, Center, and LFE-Out output jacks are often disposed in a single
apparatus. As a result, an electronic device such as an audio card (i.e., a sound
10 card) usually needs a jack detector to detect the state of each jack in order to
detect whether external terminals are inserted into the output jacks.

FIG. 1 is a schematic illustration showing the connection between a control
unit and multiple phone-jacks. As shown in FIG. 1, the control unit 11 mainly
outputs audio signals to each of the phone-jacks PJ1, PJ2 and PJ3, and detects the
15 connection state of each jack. The jack PJ1 outputs main audio signals (Line-out
R & L), the jack PJ2 outputs LFE-out audio signals (LFE-out) and the center
output audio signals (CEN-out), and the jack PJ3 outputs surround audio signals
(Surround-out R & L). Each of the phone-jacks PJ1, PJ2 and PJ3 of the system
has at least one switch (e.g., pins 2 and 3 of each jack) to indicate the insertion
20 states of the external terminals. Because in FIG. 1 the system has three
phone-jacks PJ1, PJ2 and PJ3, the control unit 11 needs three I/O pins DT1, DT2

and DT3 to receive insertion state signals of the phone-jacks PJ1, PJ2 and PJ3. If the system has five phone-jacks, the control unit 11 needs five I/O pins to receive the insertion state signals of the five jacks. In the integrated circuit (IC) manufacturing processes, the more the number of I/O pins is, the more the manufacturing process costs. Therefore, if the number of I/O pins is reduced, the manufacturing cost of the control unit may be decreased.

SUMMARY OF THE INVENTION

It is therefore one of the many objects of the invention to provide a multi-jack detector for detecting states of jacks using a single I/O pin according to impedance distribution.

To achieve the above-mentioned object, a multi-jack detector for detecting states of a plurality of jacks is disclosed. Each jack comprises a first switch having a first normally closed terminal and a first output terminal. The multi-jack detector comprises a plurality of bias resistors each coupled to one of the first output terminals, respectively; a control unit for determining the states of the plurality of jacks; wherein the first normally closed terminals are commonly coupled to a first node and the control unit determines the states of the plurality of jacks according to a voltage at the first node.

Because the voltage at the first node is different for each state of the jacks, the detector can detect the states of the jacks using a single I/O pin.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic illustration showing the connection between a control unit and multiple phone-jacks.

FIG. 2 shows a multi-jack detector applied to multiple phone-jacks

according to a first embodiment of the invention.

FIG. 3 is a partial block diagram showing an equivalent circuit and the control unit.

FIG. 4 shows the resistance of the load resistor R_L and the magnitude of the
5 input voltage V_{in} corresponding to the states of the phone-jacks PJ1, PJ2 and PJ3.

FIG. 5 shows a multi-jacks detector applied to multiple phone-jacks according to a second embodiment of the invention.

DETAILED DESCRIPTION OF THE INVENTION

The multi-jack detector of the invention will be described hereinafter with
10 reference to the accompanying drawings.

FIG. 2 shows a multi-jack detector applied to multiple phone-jacks according to a first embodiment of the invention. Referring to FIG. 2, an audio signal output system includes three phone-jacks PJ1, PJ2 and PJ3, and a control unit 21. The phone-jacks PJ1, PJ2 and PJ3 have pins 1 and 4 serving as output
15 terminals for audio signals, pins 5 serving as grounded terminals, and pins 2 and 3 serving as NC (normally closed) terminals. When an external terminal is not inserted into the phone-jack, the NC terminal is electrically connected to the output terminal. When the external terminal is inserted into the phone-jack, the NC terminal is not electrically connected to the output terminal. The pins 1 and
20 4 of the phone-jack PJ1 are grounded via a bias resistor R1 and a matching resistor R2, respectively. The pins 1 and 4 of the phone-jack PJ2 are grounded via a bias resistor R3 and a matching resistor R4, respectively. The pins 1 and 4

of the phone-jack PJ3 are grounded via a bias resistor R5 and a matching resistor R6, respectively. The matching resistors R2, R4 and R6 are resistors for matching the two output terminals of each jack, and have resistances equal to those of the bias resistors R1, R3 and R5, respectively. Of course, if resistance
5 matching is not an issue, the matching resistors may also be omitted. The pins 2 of the phone-jacks PJ1, PJ2 and PJ3 are connected together, and connected to a state detection I/O pin (I/O Pin) DT1 of the control unit 21 via a filter resistor Rf, which may also be omitted. If the resistance of each bias resistor is properly selected to make the voltages at the I/O pin DT1 in various states different from
10 each other or one another, the system may detect the terminal insertion state of each of the phone-jacks PJ1, PJ2 and PJ3 using a single I/O pin, thereby reducing the number of I/O pins.

FIG. 3 is a partial block diagram showing an equivalent circuit of the multiple phone-jacks and the control unit 21 in FIG. 2. As shown in FIG. 3, the
15 equivalent circuit obtained by viewing outwardly from the detection pin DT1 of the control unit 21 includes a pull-up resistor R_p, a filter resistor R_f and a load resistor R_L, which are connected in series, and a filter capacitor C_f, which is connected in parallel with the filter resistor R_f and the load resistor R_L, wherein the load resistor R_L is defined as the resistance by viewing outwardly from the
20 filter resistor R_f. If the resistance of the filter resistor R_f is far smaller than that of the load resistor R_L, the filter resistor R_f may be neglected. Thus, the input voltage V_{in} may be regarded as a bias voltage between the pull-up resistor R_p and

the load resistor R_L . Because the resistances of the load resistor R_L are different in various connection states of the jacks, the detected input voltages V_{in} at the pin DT1 are also different. Consequently, the control unit 21 according to this embodiment of the invention utilizes the converter 41 to convert the input voltage V_{in} at the detection pin DT1 into a decoding signal, and then utilizes the decoder 42 to generate detection signals S1, S2 and S3 according to the decoding signal. The converter 41 may be an analog-to-digital converter.

If the resistances of the bias resistors R_1 , R_3 and R_5 are $2R$, $4R$ and $8R$, respectively, the resistance of the pull-up resistor R_p is R , and the voltage source V_{dd} is $5V$, then the listing of the states of the phone-jacks PJ1, PJ2, and PJ3 corresponding to the resistance of the load resistor R_L and the magnitude of the input voltage V_{in} are shown in FIG. 4. Because there are three phone-jacks PJ1, PJ2 and PJ3, there are eight connection states of the jacks in total. The states are described in the following.

In state 0, there is no external terminal being inserted into the phone-jacks PJ1, PJ2 and PJ3. Therefore, the equivalent resistance formed by the phone-jacks PJ1, PJ2 and PJ3 equals to that of the bias resistors R_1 , R_3 and R_5 connected in parallel. That is, the load resistor R_L is $8/7R$ and the input voltage V_{in} is $2.67V$.

In state 1, there is an external terminal being inserted into the phone-jack PJ3. Therefore, the equivalent resistance formed by the phone-jacks PJ1, PJ2 and PJ3 equals to that of the bias resistors R_1 and R_3 connected in parallel. That is,

the load resistor R_L is $8/6R$ and the input voltage V_{in} is 2.86V.

In state 2, there is an external terminal being inserted into the phone-jack PJ2. Therefore, the equivalent resistance formed by the phone-jacks PJ1, PJ2 and PJ3 equals to that of the bias resistors R_1 and R_5 connected in parallel. That is,
5 the load resistor R_L is $8/5R$ and the input voltage V_{in} is 3.08V.

In state 3, there are two external terminals being inserted into the phone-jack PJ2 and PJ3, respectively. Therefore, the equivalent resistance formed by the phone-jacks PJ1, PJ2 and PJ3 equals to that of the bias resistor R_1 . That is, the load resistor R_L is $8/4R$ and the input voltage V_{in} is 3.33V.

10 In state 4, there is an external terminal being inserted into the phone-jack PJ1. Therefore, the equivalent resistance formed by the phone-jacks PJ1, PJ2 and PJ3 equals to that of the bias resistors R_3 and R_5 connected in parallel. That is, the load resistor R_L is $8/3R$ and the input voltage V_{in} is 3.64V.

In state 5, there are two external terminals being inserted into the phone-jack PJ1 and PJ3, respectively. Therefore, the equivalent resistance formed by the
15 phone-jacks PJ1, PJ2 and PJ3 equals to that of the bias resistor R_3 . That is, the load resistor R_L is $8/2R$ and the input voltage V_{in} is 4V.

In state 6, there are two external terminals being inserted into the phone-jack PJ1 and PJ2, respectively. Therefore, the equivalent resistance formed by the
20 phone-jacks PJ1, PJ2 and PJ3 equals to that of the bias resistor R_5 . That is, the load resistor R_L is $8/1R$ and the input voltage V_{in} is 4.4V.

In state 7, there are three external terminals being inserted into the

phone-jack PJ1, PJ2 and PJ3, respectively. Therefore, the equivalent resistance formed by the phone-jacks PJ1, PJ2 and PJ3 is infinite. That is, the load resistor RL is cut off and the input voltage Vin is 5V.

5 In this embodiment, when the detection signal S1 is H, it means that an external terminal is inserted into the phone-jack PJ1. The same interpretation can be applied to the output states of the detection signals S2 and S3 and will be readily appreciated by one skilled in the art without further descriptions.

Consequently, it can be understood from FIG. 4 that the resistances of the load resistor RL and the input voltages Vin are different no matter which of the
10 phone-jacks PJ1, PJ2 and PJ3 has been inserted with an external terminal. So, the control unit 21 is capable of detecting which of the phone-jacks PJ1, PJ2 and PJ3 has been inserted with an external terminal accordingly.

FIG. 5 shows a multi-jack detector applied to multiple phone-jacks according to a second embodiment of the invention. In the first embodiment of
15 FIG. 2, the pins 2 of the phone-jacks PJ1, PJ2 and PJ3 are connected together. However, in the second embodiment of FIG. 5, the pins 2 of the phone-jacks PJ1, PJ2 and PJ3 are coupled together through adjusting resistors R7, R8 and R9, respectively. By utilizing resistors positioned at different locations, such as R1, R3, R5 at pin 1's, R2, R4, R6 at pin 4's, and R7, R8, R9 at pin 2's, the resistances
20 needed may be adjusted with more flexibility. In the second embodiment, for example, the resistances of the bias resistors R1, R3 and R5 and the pull-up resistor Rp are set to be R, and the resistances of the adjusting resistors R7, R8

and R9 are set to be R, 3R and 7R, respectively. Thus, it is possible to generate different load resistances and input voltages under different states.

While certain exemplary embodiments have been described and shown in the accompanying drawings, it is to be understood that such embodiments are
5 merely illustrative of and not restrictive on the broad invention, and that this invention not be limited to the specific construction and arrangement shown and described, since various other modifications may occur to those ordinarily skilled in the art.